



If caregivers have a choice, they choose Lopital



Periodical preventative
maintenance and inspection

Elexo XXL Shower-toilechair

Elexo XXL Shower-Toilechair

51005300



Important!

The Elexo XXL must be serviced and inspected at least once a year.

Service and maintenance of the Elexo XXL is only permitted by qualified persons and using original spare parts.

Making changes to the construction could affect the safety of the Elexo XXL. This will also lead to Lopital's liability and warranty conditions being invalidated. As a result, the Elexo XXL will no longer comply with the regulation MDR (EU) 217/745 for medical devices.

Each inspection or repair must be entered to the log.

The average technical life of the Elexo XXL is 10 years, assuming it is cleaned daily and regularly maintained supplied.

Manufacturer:

Lopital Nederland B.V.
Laarakkerweg 9, 5061 JR Oisterwijk, the Netherlands
T +31 (0)13 5239300
www.lopital.com, info@lopital.nl

Contents

1. General condition of the chair.....	4
2. Batteries.....	5
3. Battery charger	6
4. Operation and Lock button.....	7
5. Wheels.....	8
6. Arm rests.....	10
7. Footrests.....	11

1. General condition of the chair
2. Batteries
3. Charger
4. Operation + Emergency stop
5. Wheels
6. Armrest
7. footrest

C= Check

S= Service/lubricate

A= Replacement advised

V= Replacement



Month	12	24	36	48	60	72	84	96	108	120
General condition	C	C	C	C	C	C	C	C	C	C
PUR	C	C	C	C	A	C	C	C	C	A
Batteries	C	C	A	C	C	A	C	C	A	C
Charger	C	C	C	C	C	C	C	C	C	C
Operation	C	C	C	C	C	C	C	C	C	C
Wheels	C	C	C	C	C	C	C	C	C	C
Armrest	C	C	C	C	C	C	C	C	C	C
Footrest	C	C	C	C	A	C	C	C	C	A

1. General condition of the chair

Month	12	24	36	48	60	72	84	96	108	120
	C	C	C	C	A	C	C	C	C	A

Required tools

- Touch- up pen Sikkens A77A2

- Visually check if all labels are present and legible.
 - o Serialnumberlabel:
 - Is the serial number still legible?
 - Is the datamatrix still readable for a scanner?
 - Is the CE logo still visible?
 - o Inspectionlabel:
 - Is the inspection date still legible?
 - o QR label:
 - Is the QR code still readable for a QR scanner?
- Visually check all painted parts for damage and corrosion. Touch up if necessary.
- Check PUR parts for severe discolouration (Brown in particular) and damage.
- Are all the screws present and securely fitted? Also that of the guide?
- Check whether the screws of the actuator are securely fitted, both at the top and at the bottom.
(See figure 1 and 2)



Figure 1 Screw actuator




Figure 2 Screw actuator



Figure 3 Retaining rings

- Motor cover still present and not torn?
- Check whether all the retaining rings are present (8 in total). If not present then it should be placed, otherwise rejected the chair. (See figure 3)
- Does the chair move up and down smoothly?

For reasons of hygiene, it is strongly recommended to replace the seat and back once every 5 years.

Present:

- Footrests (not a failure item)
- Charger

2. Batteries

Month	12	24	36	48	60	72	84	96	108	120
	C	C	A	C	C	A	C	C	A	C

Required tools

- Battery tester
- Contactspray

- A battery can be checked only when it is charged! Measure batteries individually.
- Replace if $\leq 4,5\text{Ah}$ ($\leq 65\%$)
- Always replace both batteries.
- Write the replacement date on the battery (waterproof pen) and put a new sticker on the rear of the motor cover.

It is strongly recommended to replace the battery once every 3 years.

Method:

Put the chair in a high position and detach the plug from the manual controls.

1. Remove pressure nails at the front (2x).



Figure 4 Cap front

2. Unscrew screws at the back (2x) and detach end covers.



Figure 5 Cap Back

Please note: the charger connector is attached to the cover.

3. The front part of the battery cover can now be tilted up.



Figure 6 Battery cap

4. Replace batteries. Write the replacement date on the battery. Connect all the cables; the red positive pole should be connected last. Refit cap and secure. Test chair.

3. Battery charger

Month	12	24	36	48	60	72	84	96	108	120
	C	C	C	C	C	C	C	C	C	C

Required tools

- NEN 3140 Test equipment

- The charger must be tested each year in accordance with NEN 3140 and provided with an identification sticker and NEN 3140 sticker.
- Check charger for any damage (plug + cable + contact); if the cable is damaged, replace the whole charger.
- Check the charging voltage; it should be at least the value as indicated on the charger, and be more than 27 Volt.
- Check whether there is too much corrosion on the connectors; also check the charger connector on the chair.



Figure 7 Charger




Figure 8 Charge plug

4. Operation and Lock button

Month	12	24	36	48	60	72	84	96	108	120
	C	C	C	C	C	C	C	C	C	C

Required tools

-

- Check manual controls and cable for any damage.
- Check whether all the buttons function properly.
- Check all functions. Also pay attention to any noise (rattling /squeaking) and any jolting/faltering.
 - Fully up/down (controls switching off at maximum position).
- The chair should go into "sleep mode" when the charger is connected.
- Check emergency lowering button.
- Check the function of lowering safety device:



Figure 9 Emergency stop



Figure 10 Emergency



Figure 11 Manual control

Method:

- Put the chair on the brake.
- Block the downward movement of the chair by putting something (e.g. a beam) between the floor and the chair support / scissor mechanism, and check whether the chair switches itself off (you should hear a "click").
- Ensure that the downward movement stops.
- Check the left and right section of the scissor mechanism separately.

5. Wheels

Month	12	24	36	48	60	72	84	96	108	120
	C	C	C	C	C	C	C	C	C	C

Required tools

- Allen key 8mm

New version: From serialnumber 5300.18.050




Figure 12 Wheel



Figure 13 Wheel exploded view

- Check the attachment of the wheel (Tolerance)
- Check freewheel function + brakes.
- Do all four the wheels touch the floor on a flat surface? If not, check the chair right course.
- Brake lip intact?
- Check the tread.

Replace the wheels if they are damaged or worn.

The serial numbers 5300.18.020 to 5300.18.049 Are mounted with the new wheels (double roll) and an adapter set. These chairs still use the old frame (5800-11.8)

Old version: Before serialnumber 5300.18.020



Figure 14 Wheel




Figure 15 wheel exploded view

- Check the attachment of the wheel (Tolerance)
- Check freewheel function + brakes.
- Do all four the wheels touch the floor on a flat surface? If not, check the chair right course.
- Brake knob intact?
- Unlocking lip intact?
- Check the tread.

Replace the wheels if they are damaged or worn.

6. Arm rests

Month	12	24	36	48	60	72	84	96	108	120
	C	C	C	C	C	C	C	C	C	C

Required tools

- Allen key 6mm

- Inspect its functioning, and check for any damage, corrosion. Always treat corrosion.
- Check its room for motion, measured at the front point.
- Are the arm supports evenly positioned?

Look for an exploded view on www.lopital.nl



Figure 16 Armrest

7. Footrests

Month	12	24	36	48	60	72	84	96	108	120
	C	C	C	C	A	C	C	C	C	A

Required tools

- Allan key 4mm

New version: From serialnumber 5300.20.005

Chairs from this serial number are equipped with a height-adjustable footrest.

- Check for any damage.
- Are the foot plates evenly fitted and slanting upwards a little towards the middle?
- Check the height-adjustment, check for any damage.



Figure 17 Footrest

It is strongly recommended to replace the footplates every 5 years, due to hygiene.

- Check for any damage.
- Are the foot plates evenly fitted and slanting upwards a little towards the middle?



Figure 18 Footrest

For questions about the maintenance protocol, contact Lopital (telephone +31 (0)13 5239300 or mail info@lopital.nl). You will need the serial number (outlined in red) to inform Lopital. See the serial number label on the product for this number.

 lopital®		MD -----		
 Laarakkerweg 9 5061 JR Oisterwijk The Netherlands T: (031)13-5239300		REF -----		
IPX- Weight: -- kg Type battery: --- Drives operates: -- V Charge: ---V--- mA Non continuous: -----		SN -----		
		 --- KG/---LBS  -----		
				
		Revision -		(01)----- (11)----- (21)-----



If caregivers have a choice, they choose Lopital



For more information, visit our website: www.lopital.com

Lopital Nederland B.V. Laarakkerweg 9, 5061 JR Oisterwijk, Postbus 56, 5060 AB Oisterwijk
Tel +31 (0)13 5239300, E-mail info@lopital.nl, www.lopital.com

MAIN 5300-2024-01